

**POINTERS RUN ELEMENTARY SCHOOL  
SYSTEMIC RENOVATION**

**ADDENDUM NO. 5**

DATE: April 18, 2019

ARCHITECT: Smolen, Emr, Ilkovitch Architects, Inc.  
9211 Corporate Blvd, Suite 340  
Rockville, Maryland 20850  
Phone: (301) 770-0177  
Fax: (301) 330-3224

OWNER: Howard County Public School System

PROJECT: Pointers Run Elementary School Systemic Renovation  
Clarksville, Maryland  
Architect Project No. 17015

TO: All Prospective Bidders

The following changes are made a part of the Drawings and Specifications for the subject project, dated October 10, 2018. Receipt of this Addendum is to be acknowledged, in the space provided in the Bid Form. Failure to do so may subject the Bid to be considered as non-responsive.

**A. REQUESTS FOR INFORMATION**

- None

**B. CHANGES TO SPECIFICATIONS**

- 26 24 16 – Panelboards
  - o **ADD** section in its entirety with Attached

**C. CHANGES TO DRAWINGS**

- None

**D. ATTACHMENTS**

- None

**END OF ADDENDUM NO. 5**

**SECTION 26 24 16 - PANELBOARDS**

**PART 1 - GENERAL**

1.1 SECTION INCLUDES

- A. Circuit breaker panelboards, distribution and lighting and appliance branch-circuit types.

1.2 RELATED SECTIONS

- A. Identification for electrical systems: Section 26 05 53.

1.3 REFERENCES

- A. ANSI/NECA 407: Recommended Practice for Installing and Maintaining Panelboards.
- B. NEMA 250: Enclosures for Electrical Equipment (1000 Volts Maximum).
- C. NEMA PB 1: Panelboards.
- D. NEMA PB 1.1: Proper Installation, Operation, and Maintenance of Panelboards Rated 600 Volts or Less.
- E. NETA ATS: Acceptance Testing Specifications for Electrical Power Distribution Equipment and Systems.
- F. UL 50: Enclosures for Electrical Equipment.
- G. UL 67: Panelboards.

1.4 DEFINITIONS

- A. Circuit-breaker panelboards in this section:
  - 1. Distribution panelboard: Capable of accepting up to 1200-A branch breakers.
  - 2. Lighting and appliance panelboard: Maximum branch breaker amperage 125 A for 277/480V and 100A for 120/208V.

1.5 SUBMITTALS

- A. Product data: For each type of panelboard, overcurrent protective device, accessory, and component indicated.
- B. Bill of materials: Provide detailed list of components.
- C. Shop drawings: For each type of panelboard, include the following details:
  - 1. Dimensioned plans, elevations, sections, and details. Show tabulations of installed devices, equipment features, and ratings in panel schedule format.
  - 2. Detail enclosure types and details for types other than NEMA 250, Type 1.
  - 3. Detail bus configuration, current, and voltage ratings.
  - 4. Short-circuit current rating of panelboards and overcurrent protective devices.
  - 5. Features, characteristics, ratings, and factory settings of individual protective devices and auxiliary components.

**POINTERS RUN ELEMENTARY SCHOOL  
SYSTEMIC RENOVATION**

- D. Operation and Maintenance Data: For panelboards and components to include in operation and maintenance manuals. In addition to items specified in Division 01 and Section 26 01 01, include the following:

- 1. Manufacturer's written instructions for testing and adjusting overcurrent protective devices.
- 2. Copy of each printed panelboard schedule representing final version following installation.

1.6 QUALITY ASSURANCE

- A. Source limitations: Obtain panelboards, overcurrent protective devices, components, and accessories through one source from a single manufacturer.
- B. Electrical components, devices, and accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency accepted by the authority having jurisdiction, and marked for intended location and application; listed as a complete assembly.
  - 1. UL label and local testing (where required): As specified in Section 26 05 00, Common Work Results for Electrical.
- C. Comply with referenced standards and listings previously identified including NEMA PB 1, NFPA 70, and UL 67.

1.7 COORDINATION

- A. Coordinate layout and installation of panelboards and components with other construction that penetrates walls or is supported by them, including electrical and other types of equipment, raceways, piping, encumbrances to workspace clearance requirements, and adjacent surfaces. Maintain required workspace clearances and required clearances for equipment access doors and panels.

1.8 DELIVERY, STORAGE, AND HANDLING

- A. Store equipment indoors in clean dry space with uniform temperature to prevent condensation. Protect equipment from exposure to dirt, fumes, water, corrosive substances, and physical damage.

1.9 PROJECT CONDITIONS

- A. Interruption of existing electrical service: Do not interrupt electrical service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electrical service according to requirements indicated:
  - 1. Notify Architect no fewer than seven days in advance of proposed interruption of electrical service. Provide applicable details of proposed outage including sequence of work and methods of providing temporary electrical service.
  - 2. Do not proceed with interruption of electrical service without written permission.

1.10 EXTRA MATERIALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
  - 1. Keys: Two spares for each type of panelboard cabinet lock.
  - 2. Furnish spare breakers for panelboards as indicated in schedule on drawings.

## PART 2 - PRODUCTS

### 2.1 ACCEPTABLE MANUFACTURERS

- A. Basis-of-design product: Subject to compliance with requirements, provide scheduled Schneider Electric; Square D products panelboards or comparable product by one of the following:
  - 1. Eaton Corporation
  - 2. General Electric Company
  - 3. Schneider Electric; Square D products

### 2.2 PANELBOARDS, GENERAL

- A. UL listing: UL 67, listed and labeled.
- B. Integrated equipment short-circuit rating: Each panelboard, as a complete unit, shall have a short-circuit rating equal to or greater than the integrated equipment rating shown or scheduled on the drawings.
  - 1. Rating shall be established by testing in accordance with UL 67, with the overcurrent devices mounted in the panelboard. Make short-circuit tests on the overcurrent devices and on the panelboard structure simultaneously, by connecting the fault to each overcurrent device with the panelboard connected to its rated voltage source. The source shall be capable of supplying specified panelboard short-circuit current or greater.
  - 2. Testing of overcurrent devices only while individually mounted is not acceptable. Testing the bus structure by applying a fixed fault to the bus structure alone is not acceptable.
  - 3. Mark each panelboard with its maximum short-circuit current rating at the supply voltage.
  - 4. Series rating of panelboards with devices outside of the panelboard enclosure are not permitted.
- C. Enclosures: Flush- or surface-mounted as indicated, NEMA PB 1, Type 1, UL 50, galvanized steel.
  - 1. Size: Where multiple-width or multiple-section panelboards are indicated or required, each cabinet shall be the same width and height.
  - 2. Provide enclosure type as indicated below or listed on drawings:
    - a. Indoor Dry and Clean Locations: NEMA 250, Type 1.
- D. Directory card: Inside panelboard door, mounted in metal frame with transparent protective cover with information as indicated in Part 3, Identification.
- E. Provisions for future devices: Mounting brackets, bus connections, filler plates, and necessary appurtenances required for future installation of devices.
- F. Furnish each unit with a master nameplate, listing standard manufacturer information including voltage, ampacity, frequency, and short-circuit ratings; manufacturer's model and project designations.

### 2.3 CIRCUIT-BREAKER PANELBOARDS

- A. Factory-assembled complete with breakers.
- B. Cabinets and fronts: Minimum 20 inches wide, wiring gutter space in accordance with UL 67, with minimum four-inch width on every side.

**POINTERS RUN ELEMENTARY SCHOOL  
SYSTEMIC RENOVATION**

1. Cabinet front: Hinged trim with entire front hinged to cabinet box with piano hinge and screw fasteners for surface mounted cabinets. Door-in-door construction, one or more latches as required for size, with outer door covering the gutter.
  2. Door: Required for sizes up to and including 600 amps.
    - a. Lock: Flush, cylinder tumbler type, with catch and spring-loaded stainless steel door pull. All panelboards shall be keyed alike. Provide two keys per lock. Provide extra keys as required in "Extra Materials" in Part 1 above.
    - b. Hinges: Steel, completely concealed.
- C. Circuit breakers: UL 489; voltage, continuous-current rating, and interrupting rating as indicated on the drawings.
1. Breakers shall be 1-, 2- or 3-pole, with an integral crossbar to ensure simultaneous opening of all poles in multipole circuit breakers.
  2. Operating mechanism: Over center, trip-free, toggle-type with quick-make, quick-break action. Handles shall have on, off, and tripped positions.
  3. Circuit breakers shall be able to be installed in the panelboard without requiring additional mounting hardware or disturbing adjacent units, bars, or branch circuit connections.
  4. Where indicated on the drawings, provide shunt-trip main breakers, standard main breakers, or lugs.
  5. Main and branch circuit breakers shall have device ampacity rating engraved on the front or side of each breaker handle. The breaker rating shall be clearly visible without removing panelboard cover.
  6. Circuit breakers shall be rated for use with 75 deg C wire (conductor temperature rating).
  7. Thermal-magnetic circuit breakers: Inverse time-current element for low-level overloads, and instantaneous magnetic trip element for short circuits. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 amps and larger.
  8. Ground-fault circuit interrupter (GFCI) type circuit breakers: Single- and two-pole configurations with Class A ground-fault protection (6-mA trip).
  9. Tandem breakers are not permitted.
- D. Bussing assembly and temperature rise: Panelboard bus structure and main lugs or main circuit breaker shall have current ratings as shown on the panelboard schedule, established by heat rise tests conducted in accordance with UL 67.
1. Conductor dimensions shall not be accepted in lieu of actual heat tests.
  2. Current-carrying parts of the bus structure shall be hard-drawn copper, 98 percent conductivity.
  3. Provide a separate ground bus with screw terminals for branch wiring and feed-through lugs.
- E. Distribution panelboards: Distribution panelboard shall be capable of accepting up to 1200 ampere branch breakers, or as indicated on drawing panel schedules. Current characteristics shall be as scheduled on the drawings.
- F. Branch circuit panelboards: Panelboard shall be capable of accepting up to 100-amp branch breakers.
1. Single-pole, 15 and 20 A circuit breakers intended to switch fluorescent lighting loads on a regular basis shall carry the SWD marking.
  2. Branch breakers serving exit lights, fire alarm, emergency lighting shall be provided with handle-blocking devices which shall prevent accidental operation but not prevent tripping.

2.4 SOURCE QUALITY CONTROL

**POINTERS RUN ELEMENTARY SCHOOL  
SYSTEMIC RENOVATION**

- A. With branch circuit breakers installed, short-circuit test panelboards as complete units, in accordance with requirements of UL 67.

**PART 3 - EXECUTION**

**3.1 INSTALLATION**

- A. Securely attach panelboards to the wall where indicated on the drawings. Install in accordance with NEMA PB 1.1 and manufacturer's written installation instructions.

- 1. Mounting height:

- a. 72 inches (1829 mm) to top of panelboard.
- b. Panelboards taller than 72 inches (1829 mm): Bottom edge no more than 4-inches (102 mm) above floor.
- c. Top breaker maximum height: No more than 6-feet, 7-inches (2.0 m) above the floor or working platform.

- B. Comply with applicable portions of NECA 407.
- C. Frame and mount printed circuit directory indicating type and location of equipment on each circuit.
- D. Wiring in gutters: Arrange conductors into groups, and bundle and wrap with wire ties.
- E. Install filler plates in unused spaces.

**3.2 CONNECTIONS**

- A. Connect panelboards and components to wiring and to ground as indicated.
- B. Shared neutral conductors shall not be permitted, except where indicated.
- C. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. Where manufacturer's values are not indicated, use those specified in UL 486A and UL 486B.

**3.3 IDENTIFICATION**

- A. Materials: Refer to Division 26 Section "Identification for Electrical Systems." Identify units, auxiliary devices, controls, and wiring. Identify equipment ratings.
- B. Nameplates: Refer to Division 26 Section "Identification for Electrical Systems" for additional requirements. Provide identification nameplate for each panelboard and associated components located on front of assembly.
- C. Identify field-installed wiring and components. Refer to Division 26 Section "Identification for Electrical Systems" for additional requirements.
- D. Provide printed directory for each panelboard. Handwritten directories are not acceptable. Copying of panel schedules and descriptions on drawings is not acceptable. Circuit directory shall reflect final circuit installation. Include the following information:
  - 1. Panelboard designation and room location.

**POINTERS RUN ELEMENTARY SCHOOL  
SYSTEMIC RENOVATION**

2. Circuit breakers, size and number of poles.
3. Circuit or feeder description including destination room name(s) and number(s).
4. Clear description of type of load circuit serves.
5. Panelboard ratings: Main bus ampacity, main circuit breaker or main lug ampacity, AIC rating.
6. Incoming primary feeder size and source panelboard circuit designation.

- E. Room names and numbers on the panelboard circuit directories shall match names and numbers used by the Owner. Note that room names and numbers on the drawings may not match the Owner's final room name and numbering scheme.

**3.4 FIELD QUALITY CONTROL**

- A. Make insulation-resistance tests of each panelboard bus, component, and connecting supply, feeder, and control circuit.
- B. Make continuity tests of each circuit.
- C. Perform each visual and mechanical inspection and electrical test stated in NETA Acceptance Testing Specification. Certify compliance with test parameters.
- D. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.

**3.5 CLEANING**

- A. Clean interior and exterior of panelboards.
- B. Refinish painted surfaces damaged during construction to match the rest of the panelboard.

**END OF SECTION 26 24 16**